

CORRIGENDUM 1

6.101.7.3.3 Characteristics of supply circuit

Replace the first existing sentence of second paragraph of this subclause by the following new paragraph:

TD_{sb} and TD_{bb}: For capacitor bank switching tests, the characteristic of the supply circuit shall be such that the voltage variation (voltage increase after making, voltage decrease after breaking) is less than 2 % for TD_{sb1} and TD_{bb1} and less than 5 % for TD_{sb2} and TD_{bb2}.

6.101.7.3.3 Caractéristiques du circuit d'alimentation

Remplacer la première phrase existante du deuxième alinéa de ce paragraphe par le nouvel alinéa suivant:

TD_{sb} et TD_{bb}: Pour les essais de manœuvre de batterie de condensateurs, la caractéristique du circuit d'alimentation doit être telle que la variation de tension (augmentation de la tension après établissement, décroissance de la tension après coupure) soit inférieure à 2 % pour TD_{sb1} et TD_{bb1} et inférieure à 5 % pour TD_{sb2} et TD_{bb2}.

Figure 5 – General test circuit for three- and single-phase capacitive switching tests

Replace the existing table in the figure by the following new table:

Test duty	Power source	Z_s	TRV-control	$C1$	R_d	$C2$	$C3''$
TD _{lc1} , TD _{lc2}	1) Earthed 2) Isolated	Like TD _{load}	Like TD _{load}	-	$\leq 0,05X_C$	Earthed	1): ~2 C2 2): - not required
TD _{cc1} , TD _{cc2}	1) Earthed 2) Isolated	Like TD _{load}	Like TD _{load}	-	$\leq 0,05X_C$	Earthed	1): ~2 C2 2): - not required
TD _{sb1} , TD _{sb2}	1) Earthed 2) Isolated	sb1 $\leq 0,02X_C$ sb2 $\leq 0,05X_C$, and actual $I_{sc} \leq \text{rated } I_{sc}$	Like TD _{load}	-	-	1) Isolated or earthed 2) Earthed	-
TD _{bb1} , TD _{bb2}	1) Earthed 2) Isolated	bb1 $\leq 0,02X_C$ bb2 $\leq 0,05X_C$, and actual $I_{sc} \leq \text{rated } I_{sc}$	Not specified	1) Isolated or earthed 2): earthed	-	Like C1	-